

Rekommendationstabell för kraftkabel AKKJ / FKKJ till strömtrafo



Area (mm ²)	Strömtransformator	Dimension innerledare* Bredd x höjd (mm)
25	4R21.3	10 x 7
35	4R21.3	13 x 10
50	4R21.3	14 x 12
70	4R21.3	17 x 12
95	4R21.3 / 6A315.3	19 x 14
120	6A315.3	22 x 16
150	6A315.3	24 x 17
185	6A315.3 / 7A412.3	26 x 19
240	6A315.3 / 7A412.3	29 x 21
300	7A512.3 / 8A512.3	34 x 24

* Angivna ledarmått kan skilja mellan olika fabrikat